

# DisplayPort 1.2 to HDMI Active Converter, DisplayPort to HDMI (M/F), HDCP, 4K x 2K @ 30 Hz / 1080p @ 60 Hz, 6 in.

# MODEL NUMBER: P136-06N-UHD-V2







Converts a DisplayPort 1.2 audio and 4K x 2K video signal for display on an HDMI monitor, projector or television.

### Description

The P136-06N-UHD-V2 DisplayPort 1.2 to HDMI Active Converter connects a DisplayPort 1.2 computer to the HDMI port on a monitor, projector or television. With a male DisplayPort connector and a female HDMI connector, this converter lets you use your existing HDMI display instead of buying a new DisplayPort monitor.

Ideal for displaying crystal-clear video on a large monitor or digital sign, this converter supports Ultra High Definition (UHD) video resolutions up to 3840 x 2160 (4K x 2K) @ 24/30 Hz, as well as rich, full audio (if your DisplayPort card supports audio passthrough) and HDCP (High-Definition Content Protection). Because it's an active converter, the P136-06N-UHD-V2 converts both Single-Mode and Dual-Mode (DP++) DisplayPort output. It's perfect for use with graphics cards, such as AMD Eyefinity, that do not output DP++ signals.

Plug and play with no software, drivers or power supply needed. Gold-plated connectors and contacts ensure excellent conductivity. Integral strain relief ensures the converter and molded connectors last a long time. The P136-06N-UHD-V2 is backward compatible with previous DisplayPort generations and fits easily in a briefcase, backpack or laptop bag for connecting on the go.

### Features

### Send High-Quality DisplayPort 1.2 Audio/Video Signals to an HDMI Display

- Connects DisplayPort 1.2 computer to HDMI-enabled monitor, projector or TV
- Ideal for displaying video on large monitor or digital sign
- Female HDMI and male DisplayPort connectors

# Highlights

- Active converter works with all DisplayPorts
- Supports UHD video resolutions up to 3840 x 2160 (4K x 2K) @ 24/30 Hz
- Supports 7.1 Audio Surround Sound
- HDCP 1.3 and DPCP 1.0 compliant
- Converts both Single-Mode and Dual-Mode DisplayPort output
- Gold-plated connectors and contacts

## Package Includes

P136-06N-UHD-V2 DisplayPort
1.2 to HDMI Active Converter
(M/F), 6 in.



• Backward compatible with previous DisplayPort generations

#### Vibrant, Superior Video Quality

- Supports Ultra High Definition (UHD) video resolutions up to 3840 x 2160 (4K x 2K) @ 24/30 Hz
- Supports 7.1 Audio Surround Sound
- HDCP 1.3 and DPCP 1.0 compliant
- Converts both Single-Mode and Dual-Mode DisplayPort output
- Works with graphics cards that don't output DP++ signals, such as AMD Eyefinity

#### **Superior Materials for Superior Performance**

- · Gold-plated connectors and contacts for excellent conductivity
- Integral strain relief for long life
- Plug-and-play—no software, drivers or power supply necessary
- Fits easily into briefcase, backpack or laptop bag

# **Specifications**

OVERVIEW		
UPC Code	037332192028	
Technology	HDMI (All types); DisplayPort (all types)	
INPUT		
Cable Length (in.)	6	
Cable Length (cm)	15.24	
PHYSICAL		
Shipping Dimensions (hwd / in.)	7.000 x 9.000 x 0.500	
Shipping Dimensions (hwd / cm)	17.78 x 22.86 x 1.27	
Shipping Weight (lbs.)	0.0900	
Shipping Weight (kg)	0.04	
Color	Black	
CONNECTIONS		
Side A - Connector 1	DISPLAYPORT (MALE)	
Side B - Connector 1	HDMI (FEMALE)	
FEATURES & SPECIFICATIONS		
HDCP Specification	1.3	



WARRANTY	
Product Warranty Period (Worldwide)	3-year limited warranty

© 2018 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies